TouchControl 5 Metering meets Monitor Control



TouchControl 5, our Dante® based AoIP monitor controller with metering.

Built on our long and proud legacy of making broadcast-ready monitor controllers, TouchControl 5 features a 5" intuitive touchscreen and has a small footprint, preserving valuable space on your desktop.

TouchControl 5 is a small-sized AoIP (Audio over IP) based monitor controller, using the monitor control engine of the well-known SurroundControl. It supports the AoIP standards Dante® and AES67 and can be powered over ethernet.

It features instant control over a high channel count: up to 32 audio channels can be controlled with one single knob. Beside others, it provides a high-quality microphone input, speaker output,

headphone output and features e. g. mute/solo, metering, SPL measurement and talkback. It is for network-enabled production facilities, the classic RTW customers like broadcast facilities etc. as well as other modern recording facilities.



Product Information TouchControl 5



- 1 Configurable 5"
 Touch Display
- 2 Integrated Microphone for Talkback & SPL Measurement
- 3 Level Control with User Definable Key Functions



- 4 Audio over IP | Power over Ethernet
- 5 Studio Grade Microphone Input with 48 V
- 6 Studio Quality Headphones Outputs
- 7 Analog Line Outs for External Speakers

Key Features

- Monitoring control from Stereo to 22.2 for Dante®/AES67 Audio over IP networks
- Power over Ethernet: One cable for both audio and power (IEEE 802.3af compliant)
- Level control and metering of up to 24 (32) audio channels (24 bit, 96 kHz)
- User configurable 5" touch display
- Integrated Microphone for calibrating monitoring, SPL measurement and talkback
- RTW Metering with Premium PPM, True Peak and VU
- Tried, tested and approved SurroundControl engine
- Easy Setup with web-based Interface
- Modular license structure for attractive pricing
- Level control with user definable key functions
- Studio-grade 48 V phantom powered high-quality microphone input
- Powerful 6.3 mm headphone output and analog 3.5 mm speaker output, both with the option of monitoring a userdefined downmix
- © 10/2023 | All rights reserved. Changes without prior notice.

Standard Software

- 4-channel level control (4 x In, 4 x Out)
- Simple fader
- 2 x 2 channels (Stereo) or 4 x 1 channel (Mono) control
- Basic PPM with TP and Phase

Basic Unit

Table-top unit TouchControl 5, order item: 320517ND

Available Software Licenses

Multichannel, order item: SW32001

Loudness & SPL, order item: SW32002

Premium Metering, order item: SW32006

Monitor Control, order item: SW32010

Bass Management & ImmersivePlus, order item: SW32020

Model Monitor Controller

 TouchControl 5 AoIP Monitor Controller, including basic unit and activated multichannel and monitoring licenses, order item: 320517ND + SW32001 + SW32010

Dante is a trademark or registered trademark of Audinate Pty

